

# YAMAHA Generator-EF6300iSE-5.5kVA



## Brushless generator

Maintenance free.



## Circuit breaker [Electro-thermal]

Easier 'on' & 'off' of AC output with circuit breaker.



## Voltmeter

Voltage confirmation at a glance.



## Soundproof type

On all models

On some models



## Oil warning system

Engine stops automatically when oil level (pressure) has fallen below the prescribed level.



## Fuel gauge

Fuel level confirmation at a glance.



## Electric starter

Easier starting.

Brand & Model	YAMAHA, EF6300iSE
Rated Output	5.5kVA / 5.5kW
Max. Output	6.0kVA / 6.0kW
Volts	220 v
Frequency	50 Hz
Engine RPM	3000
Power Factor	1
Max. output (Amp)	27A
Starting System	Electric
Country of Origin	JAPAN

## Generator Features :

- \* YAMAHA MZ360 Engine , Durable & High performance
- \* 4-Stroke OHV Single-Cylinder Engine
- \* Computer Controlled Inverter Technology Generator
- \* Sound Level 58 dBA
- \* Greater Fuel Economy and Quietness.
- \* Economy Control System.
- \* Easy to Carry & Cold Protection Frame

Alternator General Data	
Brand	YAMAHA
Alternator Type	Brushless
Voltage Regulator	Inverter
Number of Phase	1
Protection System	Computer Controlled

Engine General Data	
Engine Brand	YAMAHA
Model	MZ360
Engine Type	4-stroke OHV
Fuel	Petrol / Octane
Fuel Tank Capacity	17
Cooling System	Air Cooled
Displacement /HP	357cc,8.4HP
Ignition System	T.C.I
Engine oil Capacity	1.1L

Generator Dimension and Noise Level	
Length	780 mm
Width	616 mm
Height	692 mm
Weight (KG)	97
Sound @7m (dBA)	58

Fuel Consumption	
Fuel Consumption @100% Load (L/H)	3.4L
Fuel Consumption @75% Load (L/H)	2.5L
Fuel Consumption @50% Load (L/H)	1.9L
Continuous Duration of Runs (H)	5

## Contact us:

ACI Motors Ltd.

Email: [al.abdullah@aci-bd.com](mailto:al.abdullah@aci-bd.com) Web: [www.acimotors.com](http://www.acimotors.com)

Contact: 01324-732639

Head office :

ACI Center, 245 Tejgaon Industrial Area ,Dhaka-1208,Bangladesh, Tel: +8802-8878603, FAX-(+8802)8878626